



## COLOUR TOUCH SCREEN WITH PLC INTEGRATED

# TSP 350



## MAIN FEATURES

- Graphic LCD display with high contrast (320x240 pixels), 3.5 ". Blue background with white written.
- Touch screen with tactile sensation and buzzer
- Until 1 Mbyte Flash memory, until 64 Kbyte data memory, 64 kbyte EEPROM memory data not volatile, 200 byte not volatile RAM memory
- N° 12 PNP digital Inputs with 4 fast inputs
- N° 12 static outputs (24VDC, 0,5 A)
- N° 4 analogic inputs for PT100, J or K Thermocouples, current or voltage
- N° 4 +/- 10 V - 12 bit analogic outputs
- Optional Ethernet port with Web Server function
- USB Slave
- N° 3 serial interface
- Standard and personalized communication protocols for PLC or other connections
- C language or AWL (instruction list) or graphic ladder programming (graphic ladder development)
- Special functions for PID regulators, step motor and electronic cams management
- Extractable terminal boards
- AC or DC power supply with large range (15/22 AC, 15/26 DC)
- Size: 145x120 mm frontal, 85 mm depth.



Reseller